

THYRISTOR SYNGL-E-PHASE POWER REGULATOR

MPI SERIES



Special Features

- Control Method Phase Control • Zero-Cross Switching Cycle Operation Control
- Multi-Input Current Voltage Contact Voltage Pulse (SSR Drive Voltage)
- You can choose either a phase control or zero-cross switching cycle operation control in both cases of contact proportion input and voltage pulse (SSR drive voltage) input
- Input/output values and many kinds of parameters are displayed
- Output soft-start / slow-up / slow-down function is equipped as a standard function. (0.00~25.0s)
- Free Voltage (100~240V AC)
- Automatic Distinction of Power Supply Frequency Range : 45~65Hz

Specification

Display

- (1) Display Type : Digital display 7-segment red LED
1+3 digits(character height 10mm)
Key function on the front panel displays values and settings.
- (2) Kinds of Display : Output value • Control input value.
Higher limit(grade) value to be set via an external device.
Lower limit value to be set via an external device

Setting

- (1) How to Set : By using keys on the front panel or an external variable resistor
- (2) Setting Parameter : Options of setting method
Phase control angle / Phase control voltage square / Zero-cross switching cycle operation control
- : Higher limit(grade)setting 0~100%
 - : Lower limit setting 0~100%
 - : Soft-start timer setting 0~25.0s
 - : Slow-up timer setting 0~25.0s
 - : Slow-down timer setting 0~25.0s
 - : Options of input method Voltage / Current / Contact / Voltage pulse
 - : Input sampling cycle setting 0 or 1~120s
(In the case of contact or voltage pulse input, 0s-setting responds to two-position control and 1s-or-more-setting responds to proportional control with the setting value double the time of proportional cycle of the regulator.)

Power Supply

- (1) Rated Voltage : 90~264V AC (free voltage)
(2) Rated Frequency : 45~65Hz

Control Input

- (1) Types of Input : I 1—Current 1 4~20mA DC
(Multi-input) Receiving impedance approx. 100Ω
- : I 2—Current 2 0~20mA DC Receiving impedance approx. 100Ω
 - : V 1—Voltage 1 1~5V DC Input impedance approx. 500kΩ
 - : V 2—Voltage 2 0~5V DC Input impedance approx. 500kΩ
 - : C 1—Contact No-voltage contact or open collector Sink load 5V 3mA DC
 - : S 1—Voltage pulse(SSR drive) 12V 3mA DC
- (the other input) : V 3—Voltage 3 0~10V DC Input impedance approx. 370kΩ

※ In the case of C1 or S1 input, the regulator responds to both two-position and proportional control.

(2) Sampling Cycle

- Contact or voltage pulse input : Two-position control 2ms
Proportional control 1~120s
- Current or voltage input : 2 / control power supply frequency

Output

- (1) Current-carrying Capacity 5 types : 20A, 30A, 50A, 70A, 100A
- (2) Output Range : 0~98% or more of an input voltage
- (3) Control Method 3 types : Phase control angle / Phase control voltage square / Zero-cross switching cycle operation control
- (4) Lowest Load Current : 0.5A(in the case of output 98%)

- (5) Applicable Load Phase Control : Resistive load
Zero-cross switching cycle operation control : Fixed resistive load

Accessory

- (1) External Variable Resistor Higher Limit(grade) : 0~100%(B10kΩ)
Lower Limit : 0~100%(B10kΩ)


- (2) Immediately-cut Fuse : External Installation

General Specification


- (1) Data Storage : Non-volatile memory(EEPROM)
- (2) Use Environment Temperature : 0~55°C(Guaranteed range for operation)
0~40°C(Guaranteed range for efficiency)
- Humidity : Below 90%Rh(No condensation)
- Altitude : 2000m above sea level max.
- Category : II
- Pollution degree : 2
- (3) Input Noise Normal : 50dB min.
Ratio of rejection Common : 100dB min.
- (4) Insulation Resistance Between input and power supply : 20MΩ min. 500V DC per minute
Between input and chassis : 20MΩ min. 500V DC per minute
- (5) Dielectric Strength Between input and output : 2300V AC per minute
Between input and chassis : 1500V AC per minute
- (6) Storage Temperature : -20~65°C
- (7) External Dimension : Refer to External dimension drawing
- (8) Weight : 20A approx. 0.6kg • 30A approx. 0.7kg
50A approx. 1.2kg
70A approx. 1.8kg • 100A approx. 2.3kg

Performance Characteristics


- Output characteristics of higher/lower limit setting and contact input
(An example of HIGH 80% and LOW 20% setting)



- Output characteristics according to control types




- Characteristics of higher limit(grade)-lower limit setting




- *1 Setting range of HIGH SET in the case of lower limit setting 20%
*2 Output characteristics in the case of HIGH SET(grade) setting 100%
*3 Output characteristics in the case of HIGH SET(grade) setting 50%

- Standard wiring




Higher limit(HIGH) and lower limit(LOW)can be set by key operation even when an external variable resistor is not installed.

- An example of three MP1s interlocked to one controller




● Soft-start/Slow-up/Slow-down function

This function restrains a sudden change of output to the load when there is a sudden change of control input or setting happening, and makes the output flow gradually.
Soft-start/Slow-up/Slow-down time is set to output 0~100%.



Ambient Temperature Characteristic Chart



Internal heating value of MP1 is approximately as follows. Follow the set-up space and use environment.

Keep in mind that the set-up site needs to be ventilated and the radiated heat needs to be relieved.

Current-carrying capacity	2 0 A	3 0 A	5 0 A	7 0 A	1 0 0 A
Heating value	2 4 W	4 0 W	5 6 W	7 9 W	1 0 9 W

Order Code Table

Item	Code	Specification		
1. Series	MP1-			
2. Control Input	M	Multi-Input	• 4~20mA DC Input Impedance approx.100Ω	• 0~20mA DC Input Impedance approx.100Ω
			• 1~5V DC Input Impedance approx. 500kΩ	• 0~5V DC Input Impedance approx. 500kΩ
3. Current-carrying Capacity	V	Voltage	• No-voltage Contact or Open Collector 5V 3mA DC	• Voltage Pulse (SSR Drive Voltage) 12V 3mA DC
			0~10V DC Input Impedance approx. 370kΩ	
			020	20A
			030	30A
			050	50A
4. Remarks	0	Without		
		With (Please consult before ordering)		

If you need accessories, chose what you need from the code table below.

(Example) MP1-M0300-A021 (As an accessory, one set of external variable resistor comes with the body.)

Accessory Code Table

5. Accessory	-A	When you want to order an accessory, put the code (-A) before an accessory code you need
6. A set of immediately-cut fuse (holder + fuse)	01A	Responding to 20A (250GH-32(32A))
	01B	Responding to 30A (250GH-40(40A))
	01C	Responding to 50A (250GH-63(63A))
	01D	Responding to 70A (250GH-100(100A))
	01E	Responding to 100A (250GH-125(125A))
7. A set of external variable resistor (variable resistor + scale + knob)	021	1 Set A set for setting a higher(grade) or lower limit
	022	2 Set A set for setting a higher(grade) and lower limit

If you need parts, chose what you need from the code table below.


Parts Code Table

Item	Code	Specification
1. Fuse Holder	250HL-17	Responding to Body 20A~100A
2. Immediately-cut Fuse	250GH-32	Responding to Body 20A (32A)
	250GH-40	Responding to Body 30A (40A)
	250GH-63	Responding to Body 50A (63A)
	250GH-100	Responding to Body 70A (100A)
	250GH-125	Responding to Body 100A (125A)


External Dimension Drawing

Body

	Exterior View	H	W	D	P1	P2	P3	R	unit : mm
20A	Figure 1	192.5±1	50±0.5	128±1	24±0.5		181±1	5.5±0.2	
30A			50±0.5	128±1	24±0.5				
50A			60±0.5	154±1	28±0.5				
70A			110±0.5	154±1		75±0.3			
100A			155±0.5	154±1		75±0.3			





Set-up Space Drawing





Accessory

External Variable Resistor



Fuse Holder



The contents of this instruction are subject to change without notice.

SHIMAX CO.,LTD.

Head Office: 11-5 Fujimi-cho, Daisen-shi, Akita 014-0011 Japan
Phone: +81-187-86-3400 Facsimile: +81-187-62-6402
E-MAIL: info@shimax.co.jp URL: http://www.shimax.co.jp